CPTW Series Control Power Transformers Compact and Economical Solutions




VOLTAGE TABLE

| VA | Primary Voltage | Secondary Voltage | Part Number |
|----------------|---------------------------------------|---------------------|----------------|
| 100 | 220 x 440, 230 x 460, 240 x 480 | 110, 115, 120 | CPTW100-AQC-F0 |
| Max Depth | Max Width | Max Height | Mounting Depth |
| 3.78" | 3.38" | 3.10" | 2.38" |
| Mounting Width | Mounting Hole Depth | Mounting Hole Width | Phase |
| 2.81" | 0.20" | 0.41" | 1 |
| Frequency | Shipping Weight | Voltage Group | |
| 50/60 Hz | 4.20 lbs. | А | |

Þ[c^• K

- ∇ R*{]^¦ÁŠã;\Áse)åÁØ*•^ÁÔ|ã;Á@•ã*@AÁ;[cÁS;&|*å^å
- ∇ CĐả ả Á ĐĐ HÁI ÁNG ÁÖ^] COMÇEDÀ @} Á ^ Á&I a Áxè ^ ÁB &I * å ^ å ÁÇ €ÁNG * ÁH €X CED
 ∇ CĐả ả Á FÁH Đ HÁI ÁNG ÁP ^ ả @ÁÇ DÁ @) Á ^ ÁB [[&\ ÁB ÁB ÁB &I * å ^ å ÁÇ FÉCÉAN à ÁHÁ [| ^ DÁÇ €ÁNG * ÁHÍ €X CED

DIAGRAM



SPECIFICATIONS

- Class 130°C (266°F) insulation system with 55°C (131°F) temperature rise.
- All transformers up to 750VA come with pre-installed secondary fuse kits. ready to accept 13/32" x 1 1/2" midget or Class CC fuses.
- Two parallel jumper links come standard with transformers with dual primary voltages.
- All transformers up to 3kVA include a built-in mounting adapter for fuse blocks.